

# Dispersion of waves in heterogeneous media

T. Dohnal, A. Lamacz, **Ben Schweizer**

TU Dortmund

Berlin, December 2015

# Physical origins of the wave equation

## Acoustics

Pressure in an ideal gas

$$\rho_0 \partial_t v + p'_0(\rho_0) \nabla \rho = 0$$

$$\partial_t \rho + \rho_0 \nabla \cdot v = 0$$

## Light

Maxwell's equations

$$\partial_t(\mu H) = -\text{curl } E$$

$$\partial_t(\varepsilon E) = \text{curl } H$$

## Elastic media

Equations of elasticity

$$\rho \partial_t^2 u + \nabla \cdot \sigma = 0$$

$$\sigma = A \nabla^s u$$

In simplified settings, each model leads to the

## Wave equation


$$\rho \partial_t^2 u = \nabla \cdot (a \nabla u)$$

with coefficients  $\rho = \rho(x)$   
and  $a = a(x)$

### Assumptions:

- Polarised  $H$ - and  $E$ -field,  $H = u(x_1, x_2)e_3$
- Constant coefficients
- Uniaxial deformation  $u = u(x_1, x_2)e_3$


# Heterogeneous media



Let  $a : \mathbb{R}^n \rightarrow (\delta, \infty)$  be 1-periodic, set  
 $a_\varepsilon(x) := a(x/\varepsilon)$

$$\partial_t^2 u^\varepsilon = \nabla \cdot (a(x/\varepsilon) \nabla u^\varepsilon(x))$$

# Heterogeneous media



Let  $a : \mathbb{R}^n \rightarrow (\delta, \infty)$  be 1-periodic, set  
 $a_\varepsilon(x) := a(x/\varepsilon)$


$$\partial_t^2 u^\varepsilon = \nabla \cdot (a(x/\varepsilon) \nabla u^\varepsilon(x))$$

**Classical homogenization):**  $u^\varepsilon \approx u$ , where  $u$  solves

$$\partial_t^2 u(x, t) = (c^*)^2 \partial_x^2 u(x, t), \quad u(x, 0) = f(x), \quad \partial_t u(x, 0) = 0$$

$$\text{Exact solution: } u(x, t) = \frac{1}{2} f(x - c^* t) + \frac{1}{2} f(x + c^* t)$$

# Heterogeneous media



Let  $a : \mathbb{R}^n \rightarrow (\delta, \infty)$  be 1-periodic, set  
 $a_\varepsilon(x) := a(x/\varepsilon)$


$$\partial_t^2 u^\varepsilon = \nabla \cdot (a(x/\varepsilon) \nabla u^\varepsilon(x))$$

**Classical homogenization):**  $u^\varepsilon \approx u$ , where  $u$  solves

$$\partial_t^2 u(x, t) = (c^*)^2 \partial_x^2 u(x, t), \quad u(x, 0) = f(x), \quad \partial_t u(x, 0) = 0$$


$$\text{Exact solution: } u(x, t) = \frac{1}{2} f(x - c^* t) + \frac{1}{2} f(x + c^* t)$$

**Observation (Experiments and Numerics):**



Initial values  $f$

# Heterogeneous media



Let  $a : \mathbb{R}^n \rightarrow (\delta, \infty)$  be 1-periodic, set  
 $a_\varepsilon(x) := a(x/\varepsilon)$


$$\partial_t^2 u^\varepsilon = \nabla \cdot (a(x/\varepsilon) \nabla u^\varepsilon(x))$$

**Classical homogenization):**  $u^\varepsilon \approx u$ , where  $u$  solves


$$\partial_t^2 u(x, t) = (c^*)^2 \partial_x^2 u(x, t), \quad u(x, 0) = f(x), \quad \partial_t u(x, 0) = 0$$

$$\text{Exact solution: } u(x, t) = \frac{1}{2} f(x - c^* t) + \frac{1}{2} f(x + c^* t)$$

**Observation (Experiments and Numerics):**



Initial values  $f$



Numerical solution for  $\varepsilon = 1/20$

# Dispersion

**Ansatz:**  $u(x, t) = U(x)e^{-i\omega t}$  with  $U(x) = e^{ik \cdot x}$

$$\partial_t^2 u = c^2 \Delta u \iff \omega^2 = c^2 |k|^2$$

**Dispersion relation:**  $\omega(k) = \pm c|k|$

**Solutions:** (here:  $x \in \mathbb{R}$ )

$$u(x, t) = \int_{\mathbb{R}} \hat{f}_{\pm}(k) e^{ikx \pm ic|k|t} dk$$

- Choosing  $\hat{f}_{\pm}$  appropriately, we can satisfy initial conditions
- Observe: solutions *depend only on*  $x + ct$  and on  $x - ct$

## Dispersion

... describes the effect that harmonic waves travel at different speeds.  
This occurs iff  $k \mapsto \omega(k)$  is not 1-homogeneous.

# The homogenization problem

**Waves** propagate in a **periodic medium**, periodicity length  $\varepsilon > 0$ .

## Variables

displacement field	$u^\varepsilon : \mathbb{R}^n \times (0, T_\varepsilon) \rightarrow \mathbb{R}$
elastic modulus	$a_Y : \mathbb{R}^n \rightarrow \mathbb{R}^{n \times n}$
initial displacement	$f : \mathbb{R}^n \rightarrow \mathbb{R}$

## Heterogeneous Wave Equation

$$\partial_t^2 u^\varepsilon(x, t) = \nabla \cdot \left( a_Y \left( \frac{x}{\varepsilon} \right) \nabla u^\varepsilon(x, t) \right)$$

$$u^\varepsilon(x, 0) = f(x), \quad \partial_t u^\varepsilon(x, 0) = 0$$

- $a_Y(\cdot) \in C^\infty(\mathbb{R}^n, \mathbb{R}^{n \times n})$  periodic for the cube  $Y := (-\pi, \pi)^n$ , i.e.  $a_Y(y) = a_Y(y + 2\pi e_i)$
- $a_Y(y)$  symmetric and positive definite matrix:  
 $a_Y(y)_{ij} = a_Y(y)_{ji}$  and  $\sum_{i,j=1}^n (a_Y(y))_{ij} \xi_i \xi_j \geq \gamma |\xi|^2$
- $f$  smooth

**Question:** What is the effective behavior of  $u^\varepsilon$  as  $\varepsilon \rightarrow 0$ ?



# Main result: $T_\varepsilon = T\varepsilon^{-2}$

We derive an effective equation for large times!

## Weakly dispersive effective equation

$$\begin{aligned}\partial_t^2 w^\varepsilon &= AD^2 w^\varepsilon + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon - \varepsilon^2 FD^4 w^\varepsilon \\ w^\varepsilon(x, 0) &= f(x), \quad \partial_t w^\varepsilon(x, 0) = 0\end{aligned}$$

Constant coefficients:

$$A, E \in \mathbb{R}^{n \times n} \text{ and } F \in \mathbb{R}^{n \times n \times n \times n}$$

$$AD^2 := \sum A_{ij} \partial_i \partial_j,$$

$$ED^2 := \sum E_{ij} \partial_i \partial_j,$$

$$FD^4 := \sum F_{ijml} \partial_i \partial_j \partial_m \partial_n$$

# Main result: $T_\varepsilon = T\varepsilon^{-2}$

We derive an effective equation for large times!

## Weakly dispersive effective equation

$$\begin{aligned}\partial_t^2 w^\varepsilon &= AD^2 w^\varepsilon + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon - \varepsilon^2 FD^4 w^\varepsilon \\ w^\varepsilon(x, 0) &= f(x), \quad \partial_t w^\varepsilon(x, 0) = 0\end{aligned}$$

Constant coefficients:

$$A, E \in \mathbb{R}^{n \times n} \text{ and } F \in \mathbb{R}^{n \times n \times n \times n}$$

$$AD^2 := \sum A_{ij} \partial_i \partial_j,$$

$$ED^2 := \sum E_{ij} \partial_i \partial_j,$$

$$FD^4 := \sum F_{ijml} \partial_i \partial_j \partial_m \partial_n$$

## Theorem (Dohnal, Lamacz, B.S., 2014 and 2015)

There exist  $A, E \in \mathbb{R}^{n \times n}$  and  $F \in \mathbb{R}^{n \times n \times n \times n}$ , computable from  $a_Y$ , s.t.

- 1 the weakly dispersive effective equation is well-posed
- 2 there holds the error estimate

$$\sup_{t \in [0, T\varepsilon^{-2}]} \|u^\varepsilon(\cdot, t) - w^\varepsilon(\cdot, t)\|_{L^2(\mathbb{R}^n) + L^\infty(\mathbb{R}^n)} \leq C_0 \varepsilon.$$

$$\text{Norm: } \|u\|_{X+Y} := \inf\{\|u_1\|_X + \|u_2\|_Y : u = u_1 + u_2\}$$

# Bloch wave analysis: Basics

1.)  $f : \mathbb{R}^n \rightarrow \mathbb{R}$  is written  
with a Fourier transform:

$$f(x) = \int_{\mathbb{R}^n} \hat{f}(\xi) e^{i\xi \cdot x} d\xi$$

# Bloch wave analysis: Basics

1.)  $f : \mathbb{R}^n \rightarrow \mathbb{R}$  is written with a Fourier transform:

$$f(x) = \int_{\mathbb{R}^n} \hat{f}(\xi) e^{i\xi \cdot x} d\xi$$

2.)  $\xi$  is written as  $\xi = k + \Theta$  with  $k \in \mathbb{Z}^n$  and  $\Theta \in Z := [-\frac{1}{2}, \frac{1}{2})^n$

$$f(x) = \int_Z \underbrace{\sum_k \hat{f}(k + \Theta)}_{=: F} e^{ik \cdot x} e^{i\Theta \cdot x} d\Theta$$

# Bloch wave analysis: Basics

1.)  $f : \mathbb{R}^n \rightarrow \mathbb{R}$  is written with a Fourier transform:

$$f(x) = \int_{\mathbb{R}^n} \hat{f}(\xi) e^{i\xi \cdot x} d\xi$$

2.)  $\xi$  is written as  $\xi = k + \Theta$  with  $k \in \mathbb{Z}^n$  and  $\Theta \in Z := [-\frac{1}{2}, \frac{1}{2})^n$

$$f(x) = \int_Z \underbrace{\sum_k \hat{f}(k + \Theta)}_{=: F} e^{ik \cdot x} e^{i\Theta \cdot x} d\Theta$$

3.)  $F = F(x; \Theta)$  is expanded in periodic eigenfunctions  $\Phi_m(x; \Theta)$ :

$$F(x; \Theta) = \sum_{m \in \mathbb{N}} \alpha_m(\Theta) \Phi_m(x; \Theta)$$

$$\begin{aligned} \Psi_m(x; \Theta) &= \Phi_m(x; \Theta) e^{i\Theta \cdot x} \text{ solves} \\ -\nabla \cdot (a(x) \nabla \Psi_m(x)) &= \mu_m(\Theta) \Psi_m(x) \end{aligned}$$

# Bloch wave analysis: Basics

1.)  $f : \mathbb{R}^n \rightarrow \mathbb{R}$  is written with a Fourier transform:

$$f(x) = \int_{\mathbb{R}^n} \hat{f}(\xi) e^{i\xi \cdot x} d\xi$$

2.)  $\xi$  is written as  $\xi = k + \Theta$  with  $k \in \mathbb{Z}^n$  and  $\Theta \in Z := [-\frac{1}{2}, \frac{1}{2})^n$

$$f(x) = \int_Z \underbrace{\sum_k \hat{f}(k + \Theta)}_{=: F} e^{ik \cdot x} e^{i\Theta \cdot x} d\Theta$$

3.)  $F = F(x; \Theta)$  is expanded in periodic eigenfunctions  $\Phi_m(x; \Theta)$ :

$$F(x; \Theta) = \sum_{m \in \mathbb{N}} \alpha_m(\Theta) \Phi_m(x; \Theta)$$

$$\Psi_m(x; \Theta) = \Phi_m(x; \Theta) e^{i\Theta \cdot x} \text{ solves} \\ -\nabla \cdot (a(x) \nabla \Psi_m(x)) = \mu_m(\Theta) \Psi_m(x)$$

**Result:** The operator  $L = -\nabla \cdot (a(\cdot) \nabla)$  acts as a multiplier:

$$Lf = L \int_Z \sum_{m \in \mathbb{N}} \alpha_m(\Theta) \Phi_m(x; \Theta) e^{i\Theta \cdot x} d\Theta = \int_Z \sum_{m \in \mathbb{N}} \alpha_m \mu_m \Phi_m(x) e^{i\Theta \cdot x} d\Theta$$

# Bloch analysis I

Bloch-transform  $f$  with basis functions  $w_m^\varepsilon$  and coefficients  $\hat{f}_m^\varepsilon(k)$

**Step 1:** The solution  $u^\varepsilon$  of  $\partial_t^2 u^\varepsilon = -L_\varepsilon u^\varepsilon$  can be represented as

$$u^\varepsilon(x, t) = \sum_{m=0}^{\infty} \int_{Z/\varepsilon} \hat{f}_m^\varepsilon(k) w_m^\varepsilon(x, k) \operatorname{Re} \left( e^{it\sqrt{\mu_m^\varepsilon(k)}} \right) dk$$

# Bloch analysis I

Bloch-transform  $f$  with basis functions  $w_m^\varepsilon$  and coefficients  $\hat{f}_m^\varepsilon(k)$

**Step 1:** The solution  $u^\varepsilon$  of  $\partial_t^2 u^\varepsilon = -L_\varepsilon u^\varepsilon$  can be represented as

$$u^\varepsilon(x, t) = \sum_{m=0}^{\infty} \int_{Z/\varepsilon} \hat{f}_m^\varepsilon(k) w_m^\varepsilon(x, k) \operatorname{Re} \left( e^{it\sqrt{\mu_m^\varepsilon(k)}} \right) dk$$

**Step 2:** Contributions of  $m > 0$  can be neglected:

$$\sup_{t \in (0, \infty)} \left\| \sum_{m=1}^{\infty} \int_{Z/\varepsilon} \hat{f}_m^\varepsilon(k) w_m^\varepsilon(x, k) \operatorname{Re} \left( e^{it\sqrt{\mu_m^\varepsilon(k)}} \right) dk \right\|_{L^2(\mathbb{R}^n)} \leq C_0 \varepsilon$$



# Bloch analysis I

Bloch-transform  $f$  with basis functions  $w_m^\varepsilon$  and coefficients  $\hat{f}_m^\varepsilon(k)$

**Step 1:** The solution  $u^\varepsilon$  of  $\partial_t^2 u^\varepsilon = -L_\varepsilon u^\varepsilon$  can be represented as

$$u^\varepsilon(x, t) = \sum_{m=0}^{\infty} \int_{Z/\varepsilon} \hat{f}_m^\varepsilon(k) w_m^\varepsilon(x, k) \operatorname{Re} \left( e^{it\sqrt{\mu_m^\varepsilon(k)}} \right) dk$$

**Step 2:** Contributions of  $m > 0$  can be neglected:

$$\sup_{t \in (0, \infty)} \left\| \sum_{m=1}^{\infty} \int_{Z/\varepsilon} \hat{f}_m^\varepsilon(k) w_m^\varepsilon(x, k) \operatorname{Re} \left( e^{it\sqrt{\mu_m^\varepsilon(k)}} \right) dk \right\|_{L^2(\mathbb{R}^n)} \leq C_0 \varepsilon$$

**Step 3:** Let  $f$  be

$$f(x) = (2\pi)^{-n/2} \int_{\mathbb{R}^n} F_0(k) e^{ik \cdot x} dk$$

with  $F_0 : \mathbb{R}^n \rightarrow \mathbb{C}$  supported on  $K \subset\subset \mathbb{R}^n$ . Then

$$\|\hat{f}_0^\varepsilon - F_0\|_{L^1(Z/\varepsilon)} \leq C_0 \varepsilon$$

## Bloch analysis II

**Step 4:** Taylor expansion of the rescaled eigenvalue

$$\mu_0^\varepsilon(k) = \frac{1}{\varepsilon^2} \mu_0(\varepsilon k) = \sum \sum A_{lm} k_l k_m + \varepsilon^2 \sum C_{lmnq} k_l k_m k_n k_q + O(\varepsilon^4)$$

For the square root we use  $\sqrt{a+c} = \sqrt{a} + \frac{1}{2\sqrt{a}}c + O(|c|^2)$

# Bloch analysis II

**Step 4:** Taylor expansion of the rescaled eigenvalue

$$\mu_0^\varepsilon(k) = \frac{1}{\varepsilon^2} \mu_0(\varepsilon k) = \sum \sum A_{lm} k_l k_m + \varepsilon^2 \sum C_{lmnq} k_l k_m k_n k_q + O(\varepsilon^4)$$

For the square root we use  $\sqrt{a+c} = \sqrt{a} + \frac{1}{2\sqrt{a}}c + O(|c|^2)$

**Proposition (Bloch-wave approximation of  $u^\varepsilon$ )**

$$v^\varepsilon(x, t) := (2\pi)^{-n/2} \frac{1}{2} \sum_{\pm} \int_K F_0(k) e^{ik \cdot x} \exp\left(\pm it \sqrt{\sum A_{lm} k_l k_m}\right) \\ \times \exp\left(\pm \frac{i\varepsilon^2}{2} t \frac{\sum C_{lmnq} k_l k_m k_n k_q}{\sqrt{\sum A_{lm} k_l k_m}}\right) dk$$

$$\sup_{t \in [0, T\varepsilon^{-2}]} \|u^\varepsilon(\cdot, t) - v^\varepsilon(\cdot, t)\|_{(L^2 + L^\infty)(\mathbb{R}^n)} \leq C_0 \varepsilon$$

Recall:  $\|u\|_{X+Y} := \inf\{\|u_1\|_X + \|u_2\|_Y : u = u_1 + u_2\}$

# Decomposition lemma

The (formal) equation for  $v$  is the “**bad Boussinesq equation**”

$$\partial_t^2 v(x, t) = AD^2 v(x, t) - \varepsilon^2 CD^4 v(x, t)$$

# Decomposition lemma

The (formal) equation for  $v$  is the “**bad Boussinesq equation**”

$$\partial_t^2 v(x, t) = AD^2 v(x, t) - \varepsilon^2 CD^4 v(x, t)$$

**Idea:** transform in a well-posed equation with a **replacement trick**

- 1 rewrite last term as  $-CD^4 = ED^2 AD^2$   
for a symmetric, positive semidefinite matrix  $E \in \mathbb{R}^{n \times n}$
- 2 replace  $AD^2$  by  $\partial_t^2$  to obtain the well-posed equation
$$\partial_t^2 w^\varepsilon(x, t) = AD^2 w^\varepsilon(x, t) + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon(x, t)$$

**It is possible that such a matrix  $E$  does not exist!**

# Decomposition lemma

The (formal) equation for  $v$  is the “**bad Boussinesq equation**”

$$\partial_t^2 v(x, t) = AD^2 v(x, t) - \varepsilon^2 CD^4 v(x, t)$$

**Idea:** transform in a well-posed equation with a **replacement trick**

- 1 rewrite last term as  $-CD^4 = ED^2 AD^2$   
for a symmetric, positive semidefinite matrix  $E \in \mathbb{R}^{n \times n}$
- 2 replace  $AD^2$  by  $\partial_t^2$  to obtain the well-posed equation  
$$\partial_t^2 w^\varepsilon(x, t) = AD^2 w^\varepsilon(x, t) + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon(x, t)$$

**It is possible that such a matrix  $E$  does not exist!**

## Lemma (Decomposability)

Let  $A \in \mathbb{R}^{n \times n}$  be symmetric and positive definite. Let  $C \in \mathbb{R}^{n \times n \times n \times n}$ . There exist symmetric and positive semidefinite  $E \in \mathbb{R}^{n \times n}$  and  $F \in \mathbb{R}^{n \times n \times n \times n}$  such that

$$-CD^4 = ED^2 AD^2 - FD^4$$

# Proof of the error estimate

**We have:**

- ①  $\sup_{t \in [0, T\varepsilon^{-2}]} \|u^\varepsilon(\cdot, t) - v^\varepsilon(\cdot, t)\|_{(L^2 + L^\infty)(\mathbb{R}^n)} \leq C_0\varepsilon$
- ②  $\partial_t^2 v^\varepsilon = AD^2 v^\varepsilon + \varepsilon^2 ED^2 \partial_t^2 v^\varepsilon - \varepsilon^2 FD^4 v^\varepsilon + O(\varepsilon^4)$

## Error estimate

Let  $u^\varepsilon$  be the solution to the heterogeneous wave equation. Let  $w^\varepsilon$  be a solution to the weakly dispersive effective equation



$$\partial_t^2 w^\varepsilon(x, t) = AD^2 w^\varepsilon(x, t) + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon(x, t) - \varepsilon^2 FD^4 w^\varepsilon(x, t).$$

Then

$$\sup_{t \in [0, T\varepsilon^{-2}]} \|u^\varepsilon(\cdot, t) - w^\varepsilon(\cdot, t)\|_{(L^2 + L^\infty)(\mathbb{R}^n)} \leq C_0\varepsilon.$$

**Proof:** Testing procedure to compare (derivatives of)  $w^\varepsilon$  and  $v^\varepsilon$ .  
Triangle inequality and interpolation lemma.

# 1-dimensional numerical results




$$\partial_t^2 w^\varepsilon = AD^2 w^\varepsilon + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon - \varepsilon^2 FD^4 w^\varepsilon$$




## 2-dimensional numerical results

### Numerical comparison:

- the original problem with  $\varepsilon$ -scale
- the dispersive equation





$u^\varepsilon$ : solution for coefficient  $a_\varepsilon$




## 2-dimensional numerical results

### Numerical comparison:

- the original problem with  $\varepsilon$ -scale
- the dispersive equation



$u^\varepsilon$ : solution for coefficient  $a_\varepsilon$




$w^\varepsilon$ : solution of weakly dispersive equation

$$\partial_t^2 w^\varepsilon = AD^2 w^\varepsilon + \varepsilon^2 ED^2 \partial_t^2 w^\varepsilon - \varepsilon^2 FD^4 w^\varepsilon$$

# Conclusions

- **Finite time:** The original problem is approximated well by the effective wave equation (no dispersion)
- **Long time**  $t \in (0, T\varepsilon^{-2})$ : Dispersive effects occur! They are effectively described by the weakly dispersive model

**Methods:** Bloch waves, replacement trick, energy estimates and interpolation



## References:

- [1] T.Dohnal, A.Lamacz, B.Schweizer: Dispersive homogenized models and coefficient formulas for waves in general periodic media. *Asymptot. Anal.* 93(1-2), 2015
- [2] T.Dohnal, A.Lamacz, B.Schweizer: Bloch-wave homogenization on large time scales and dispersive effective wave equations. *Multiscale Model. Simul.* 12(2), 2014
- [3] A.Lamacz: Dispersive effective models for waves in heterogeneous media. *Math. Models Methods Appl. Sci.* 21(9), 2011

**Thank you!**